

# Kodak Scan Station 100 Embedded Version 3.0 Configuration Organizer 3.0 07/22/08

## Installation Instructions

**You may download the new Scan Station SW and place in a temp directory or you may launch the self-executable from the web.**

**IMPORTANT!** Shut Down the Configuration Organizer before performing this update. If you launch the self-executable software update you have just down loaded, do not change the start in path, leave it set to c:\ for default installations.

It contains the following files:	
New Configuration Application ver 3.0	ConfigurationApp.exe
New Scan Station Conf ICON	configurationapp.ico
Kodak Scan Station embedded SW ver 3.0	KSS100update.exe
An ADMIN FILE to enable the SW update	kss100.xml
This Installation Instructions	KSSv3.0_installation_Instructions.pdf
Misc DLL and user Guide files	*.dll, *.pdf, *.txt, *.chm

## NEW Configuration Application 3.0

By default, the unzip utility will automatically replace the new ConfigurationApp.exe and add all the new items in the **default location** where the Kodak Scan Station 100 Configuration Organizer Application is currently installed on your PC. If you have installed the Configuration Organizer Application in a different location other than the default, then please manually place the ConfigurationApp.exe and all the other associated files in that new location and overwrite the old files.

## Updating the Scan Station to the NEW SW 3.0

- Locate these files in this path: C:\Program Files\Kodak\Scan Station 100\Embedded 3.0.0.5 KSS100 only update
- Copy the KSS100update.exe update file ver 3.0.0.5 and the kss100.xml file to a blank flash drive.
- Insert the USB flash drive into the Kodak Scan Station 100, and follow all update prompts.
- When Completed, Remove the flash drive, Then Reboot the Scan station.

Check the version of software loaded on the scan station by scrolling to the "i" icon. Once this USB pen is created with these two files, it may be used to repeat additional Scan Stations updates.

## New Features for this release are:

For last minute updates and information that we could not place on the CD, Please review the readme files also located in the update folder. For a much more detailed description and use of these new features, please review the new Administrators and Users guides also provided by this download.

- New Security Features:
  - Secure login using Lightweight Directory Access Protocol (LDAP)
  - PDF private key encryption
  - Option to enable/disable scanning to a portable USB drive
  - Ability to logout when finished
- New Enhancements for system administrators:
  - Expanded activity logging to include authenticated user information
  - Task groupings for pre-selected profiles
  - Ability to extend LDAP search to configured network folders
  - Ability to hide full network path
  - Fast scanning feature that allows scanning to begin immediately
- New Enhancements for users:
  - Ability to extend the document batch: i.e. add documents to the feeder without starting a new batch
  - Selectable OCR language
  - Ability to create individual PDF files from a multi page document batch
  - TIFF with embedded JPEG format for Health Industry related applications

## Note for Inbound and outbound FAX<sup>1</sup> capability:

<sup>1</sup>Fax Capability requires the Kodak Scan Station 100 Fax Modem Accessory and a Scan Station with a serial number higher than 45325000 - Catalog Number 128 0528 (Accessory includes: USB Cable, phone cable, and USB Modem)

Kodak Scan Station 100 with a Serial Number of 45325000 or higher is Fax Modem ready. Kodak Scan Station 100 with a Serial Number below 45325000 was not manufactured with the device drivers required for the Fax modem accessory. Therefore the FAX feature is not available with a Scan Station with a serial number below 45325000. Updating a Kodak Scan Station 100 with a serial number below 45325000 to software version 2.0 will have all the above new features available with the exception of fax. If you are interested in fax capability on your Scan Station with a serial number below 45325000, contact Kodak Service at: US&C 1-800-822-1414 or go to [www.kodak.com/go/disupport](http://www.kodak.com/go/disupport) for upgrade options. These options will vary depending what region of the world you are located.